VECTOR FRAME BANNERS
RECTANGLE-02

SET-UP NOTES

1. Redesign of this exhibit without approval by manufacture may result in dangerous and unsafe structures. The manufacture disclaims any responsibility for redesigned exhibits it does not approve in writing.

2. Parts and components such as panels and extrusions are manufactured to metric sizing. Where ever possible sizes have been noted in feet and inches as well as in metric. Below is the imperial to metric sizing table as reference. "Nominal" refers to approximate size.

IMPERIAL TO METRIC SIZES

8' Nominal = 94 1/2" or 2400mm Actual
4' Nominal = 47 1/4" or 1200mm Actual
3' Nominal = 35 7/16" or 900mm Actual
2' Nominal = 23 5/8" or 600mm Actual
1' Nominal = 11 13/16" or 300mm Actual

Code	#	Description
SL2-500	2	Support Leg
F13	4	PHFC2-900-3[35 3/8:] (Mitre / Corner Lock one end - straight cut & lock holes other end - NO Locks -)
IB2	2	END TO END LOCK CONNECTOR
CB9	4	90 DEGREE CORNER LOCK CONNECTOR
F10	2	PHFC2-900-1[35 3/8"] (Mitre / Corner Lock Both ends - No Locks)

IB2 TO PHFC2

Slide IB2 together with extrusion. Then tighten the screws to lock the IB2s together

SL2-350 TO PHFC2

LOCK HORIZONTAL EXTRUSION BY USING T- HANDLE TOOL

CB9 TO PHFC2

Slide IB2 together with extrusion. Then tighten the screws to lock the IB2s together

1. Redesign of this exhibit without approval by manufacture may result in dangerous and unsafe structures. The manufacture disclaims any responsibility for redesigned exhibits it does not approve in writing.
2. Parts and components such as panels and extrusions are manufactured to metric sizing. Where ever possible sizes have been noted in feet and inches as well as in metric. Below is the imperial to metric sizing table as reference. "Nominal" refers to approximate size.

2400mm = (94 1/2")	Phone Line / Fax
2100mm = (82 5/8")	Internet connection
1800mm = (70 7/8")	
1500mm = (59")	Outlet
1200mm = (47 1/4")	
900mm = (35 1/2")	Main Drop (point of distrution)
600mm = (23 5/8")	
300mm = (11 7/8")	

Wire running under carpet

VECTOR FRAMES BANNERS

Title: SET-UP INSTRUCTIONS

Code	#	Description
SMP-63-G	1	70.87"H X 35.43"W SINGLE SIDED DYESUB GRAPHIC (UNLINED) PRINTED ON OXFORD W/ FCE-2 ALL 4 SIDES

SMP-63-G

GRAPHIC WITH FCE-2 TO PHFC2

Install graphic by pressing the FCE-2 into the top and bottom channels of PHFC2 extrusion. To pull graphics out of the channels use tbas on the front side

1. Redesign of this exhibit without approval by manufacture may result in dangerous and unsafe structures. The manufacture disclaims any responsibility for redesigned exhibits it does not approve in writing.
2. Parts and components such as panels and extrusions are manufactured to metric sizing. Where ever possible sizes have been noted in feet and inches as well as in metric. Below is the imperial to metric sizing table as reference. "Nominal" refers to approximate size.

2400mm = (94 1/2")
2100mm = (82 5/8")
1800mm = (70 7/8")
1500mm = (59")
1200mm = (47 1/4")
900mm = (35 1/2")
600mm = (23 5/8")
300mm = (11 7/8")

Phone Line / Fax
Internet connection
Outlet
Main Drop (point of distrution)
Wire running under carpet

VECTOR FRAMES BANNERS

Title: SET-UP INSTRUCTIONS